

**Tender text Article number 353-702221**

Presence detector P42LR, 230 V, master, 2 channels, 32-37 m, IP54, for surface mounting, white



Proposed functionalities description according to BIPS 4.7.9

Presence detector P42LR, 230 V, master, 2 channels, 32-37 m, IP54, for surface mounting, white

**SPECIFICATIONS**

Configuration	master
Detector technology	PIR
Mounting method	surface mounting
Input voltage	230 Vac ± 10 %, 50 Hz
Detector output	230 V (ON/OFF)
Number of channels	2 channels
Light intensity range	20 lux – 2000 lux, ∞
Switch-off delay	pulse, 15 s – 2 h, ∞
Detection angle	360°
Detection range (PIR)	ø 37 m from a height of 3 m
Ambient temperature	-25 – +40 °C
Mounting height	2 – 3.5 m
Relay contact	2 x N.O. (max. 10 A), potential-free
Marking	CE
Protection degree	IP54

Proposed functionalities description according to BIPS 4.7.10

**Mounting method**

The detector is suitable for surface mounting on all types of ceilings.

**Configuration app**

All detectors in the installation can be configured using the app and 2-way Bluetooth® communication between a smartphone or tablet and the detector. No additional configuration tools are required. The settings can be stored as a template for other detectors. The firmware of the detector can be updated via the app.

**PIN code**

The detector can be protected with a 4-digit PIN code in the app to prevent others from controlling the detector or modifying its settings.

**Event log**

The event log in the app shows all the changes you made to the settings of a specific detector.

**Sensitivity**

The detector's sensitivity for detecting movement can be set using the app and 2-way Bluetooth® communication between a smartphone or tablet and the detector. The sensitivity can be set in 4 levels.

**Documentation**

Documentation is available in digital format on an online portal. This portal also allows to store, review and share settings in PDF and/or Excel format. The detectors can be organised into specific projects or groups. Existing detector settings can be used as a template for new detectors.

**Detection range**

The detection range is documented in accordance with EN/IEC 63180.

**Manual control with 230 V inputs**

A 230 V input wired to the detector can perform different actions: switch the light ON/OFF or switch only ON.

**Expansion of the detection area**

The detection range of the master detector can be expanded with several secondary detectors. The detectors communicate with each other via a wired or a wireless connection.

**Switch-off above lux level**

If 'Switch-off above lux level' is ON, the detector's priority is light and the second priority is movement. The detector controls the lights according to the ambient lux level. The lights will switch off when the lux level in the room is above the lux level setting for 10 min, even if there is still movement in the room. If 'Switch-off above lux level' is OFF, the detector's priority is movement. The detector controls the lights according to movement only. The lights will only switch off at the end of the switch-off delay.