

**Tender text Article number 353-701021**

Presence detector P41LR, 230 V, secondary, 32-37 m, for flush mounting (SnapFit), white



Proposed functionalities description according to BIPS 4.7.9

Presence detector P41LR, 230 V, secondary, 32-37 m, for flush mounting (SnapFit), white

**SPECIFICATIONS**

Configuration	secondary
Detector technology	PIR
Mounting method	flush-mounting (SnapFit)
Input voltage	230 Vac ± 10 %, 50 Hz
Detector output	230 V (ON/OFF)
Detection angle	360°
Detection range (PIR)	ø 37 m from a height of 3 m
Ambient temperature	-25 – +40 °C
Flush mounting depth	56.9 mm
Drill diameter	76.0 mm
Mounting height	2 – 3.5 m
Marking	CE
Protection degree	IP20

Proposed functionalities description according to BIPS 4.7.10

**Mounting method**

The detector is suitable for mounting in all types of ceilings without the use of additional elements (e.g. tiles) to guarantee stable mounting. The detector can easily be removed without damaging the ceiling or ceiling tiles.

**Configuration app**

All detectors in the installation can be configured using the app and 2-way Bluetooth® communication between a smartphone or tablet and the detector. No additional configuration tools are required. The settings can be stored as a template for other detectors. The firmware of the detector can be updated via the app.

**PIN code**

The detector can be protected with a 4-digit PIN code in the app to prevent others from controlling the detector or modifying its settings.

**Event log**

The event log in the app shows all the changes you made to the settings of a specific detector.

**Sensitivity**

The detector's sensitivity for detecting movement can be set using the app and 2-way Bluetooth® communication between a smartphone or tablet and the detector. The sensitivity can be set in 4 levels.

**Documentation**

Documentation is available in digital format on an online portal. This portal also allows to store, review and share settings in PDF and/or Excel format. The detectors can be organised into specific projects or groups. Existing detector settings can be used as a template for new detectors.

**Detection range**

The detection range is documented in accordance with EN/IEC 63180.