

# Presence or absence detector 360°, 16 m, KNX®, 3 PIR elements, flush-mounting with spring terminals, square

351-25035

4 year warranty

The presence or absence detector with two channels and daylight control for flush mounting in ceilings is suitable for switching the indoor lighting on and off. The detector is equipped with an integrated light sensor and is only compatible with KNX®.


- Combination of master/secondary possible
- Can be placed at a height of up to 6 metres
- Easy to place in false ceilings.

Presence detector for use in false ceilings, etc.

- Everything can be programmed using ETS software
- Very simple programming
- Can be programmed as a presence or absence detector
- 2 channels for setting by heliometer
  - 1 channel for turning the lighting on and off
  - 1 channel for turning the HVAC installation on and off



Detection range



h	6m	7m	8m
2 m	4 m	5 m	10 m
2.5 m	5 m	6 m	12 m
3 m	6 m	7 m	14 m
3.5 m	7 m	8 m	16 m
4 m	8 m	8 m	16 m
5 m	8 m	8 m	16 m
6 m	8 m	8 m	16 m

## Technical data

Article number	351-25035
Input voltage	30 Vdc via KNX®-bus
Detector output	KNX®
Light intensity range	5 lux – 2000 lux
Number of channels	2 channels
Switch-off delay	1 s – 255 h
Detection angle	360°
Detection range (PIR)	ø 14 m from a height of 3 m
Ambient temperature	-20 – +40 °C
Mounting method	flush-mounting
Mounting height	2 – 6 m
Dimensions visible (HxWxD)	35 mm
Dimensions (HxWxD)	88 x 88 x 55 mm
Protection degree	IP20
Marking	CE

## Dimensions

