

Swiss Garde presence detector 360°, 4 channels, 22 m, KNX, for flush-mounting box

351-25039

4 year warranty

The presence or absence detector with four channels and daylight control for flush mounting in ceilings is suitable for switching the indoor lighting on and off. The detector is equipped with an integrated light sensor and is only compatible with KNX.

- Combination of master/secondary possible
- Can be placed at a height of up to 8 metres
- - Very good and sensitive detection

Presence detector for use in meeting rooms, offices, etc.

- Everything can be programmed using ETS software
- Very simple programming
- Can be programmed as a presence or absence detector
- 2 channels for setting by heliometer
 - 1 channel for turning the lighting on and off
 - 1 channel for turning the HVAC installation on and off



Detection range

D			
2 m	5 m	6 m	12 m
3 m	7 m	8 m	16 m
4 m	9 m	9 m	18 m
5 m	10 m	10 m	20 m
6 m	10 m	11 m	22 m
7 m	10 m	11 m	22 m
8 m	10 m	11 m	22 m



KNX



master



360 °



circle, 22 m
diameter from
a height of
8 m



2 – 8 m



flush-
mounting

niko

Technical data

Article number	351-25039
Configuration	master
Input voltage	30 Vdc via KNX-bus
Detector output	KNX
Number of channels	4 channels
Detection angle	360 °
Detection range (PIR)	circle, 22 m diameter from a height of 8 m
Ambient temperature	-20 – +40 °C
Mounting method	flush-mounting
Mounting height	2 – 8 m
Dimensions visible (HxWxD)	120 x 120 x 37 mm
Dimensions (HxWxD)	120 x 120 x 48 mm
Marking	CE

Accessories

Error applying XSLT stylesheet, check console for errors