

Swiss Garde presence detector 360°, 4 channels, 22 m, KNX®, for flush-mounting box

351-25039

4 year warranty

The presence or absence detector with four channels and daylight control for flush mounting in ceilings is suitable for switching the indoor lighting on and off. The detector is equipped with an integrated light sensor and is only compatible with KNX®. Finishing colour: white

- Combination of master/secondary possible
- Can be placed at a height of up to 8 metres
- - Very good and sensitive detection

Presence detector for use in meeting rooms, offices, etc.

- Everything can be programmed using ETS software
- Very simple programming
- Can be programmed as a presence or absence detector
- 2 channels for setting by heliometer
 - 1 channel for turning the lighting on and off
 - 1 channel for turning the HVAC installation on and off



Detection range

⌈	⌈	⌈	⌈
2 m	5 m	6 m	12 m
3 m	7 m	8 m	16 m
4 m	9 m	9 m	18 m
5 m	10 m	10 m	20 m
6 m	10 m	11 m	22 m
7 m	10 m	11 m	22 m
8 m	10 m	11 m	22 m

Technical data

Article number	351-25039
Input voltage	30 Vdc via KNX®-bus
Detector output	KNX®
Number of channels	4 channels
Detection angle	360°
Detection range (PIR)	ø 22 m from a height of 8 m
Ambient temperature	-20 – +40 °C
Mounting method	flush-mounting
Mounting height	2 – 8 m
Dimensions visible (HxWxD)	120 x 120 x 37 mm
Dimensions (HxWxD)	120 x 120 x 48 mm
Marking	CE